

ER-2930W — плечевой мегафон с внеш. микрофонным входом, входом AUX, входом питания постоянного тока, звуковым сигналом (свисток) батарейного счетчика. Его можно установить на дополнительную стойку для громкоговорителя ST-16A. Недавно разработанная полиимидная диафрагма используется для обеспечения высокого качества звука.



Номер статьи:ER-2930W EU

## Specifications

Источник питания	10 x 1,5 В (R 20P)
Номинальная мощность	30 W (макс. 45 Вт)
Срок службы батареи	17 h
Сигнал работы батареи	90 min
Внеш. Вход под микрофон	600 Ом, несбалансированный разъем, ø 6,6 телефонный разъем, возможность подключения стерео, регулировка громкости
Сигналы	Свисток
Звуковой диапазон	800 м (дальность свистка 1000 м)
Размеры (Ш x В x Г)	x 512
Размеры (ø x Г)	351 x 512 mm
Покрытие	Алюминий, АБС-пластик, отлитый под давлением, светло-черный (RAL 7035 или эквивалент), серый,
Рабочая температура	от -10 °С до +40 °С

### Appearance

<Note on the audible range and battery life>

1. The indications of the audible range and battery life are based on the JEITA Standard (\*2).
2. Audible Range presumes that the megaphone employs new batteries and is used on a quiet street.  
It varies depending on such conditions as battery consumption, ambient noise, wind direction and obstacles.
3. Battery Life assumes that megaphone is used for 30 minutes a day.

